

Uputstva za demontažu izvora svjetlosti i predspojene naprave

Primjenjivo na: Intab

- 1) Izbaciti sklopku iz funkcije kako svjetiljka ne bi bila pod naponom prilikom demontaže.
 - 2) Zamaknuti leću u jednu stranu što otkriva vijak s kojim je maska spojena na svjetiljku. Isto učiniti i na drugoj strani kako bismo masku sklonili sa svjetiljke.
 - 3) Odvrnuti vijke koji drže nosač LED modula na svjetiljci. Zatim izvaditi nosač iz svjetiljke.
 - 4) Odvojiti napojni kabel od kleme pritiskom na gripere kleme te izvlačenjem žica.
 - 5) Odvojiti žicu koja je spojena na svaki LED modul i driver pritiskom na griper žice na LED modulu/driveru tankim predmetom.
 - 6) Odvrnite matice i/ili vijke koji nose driver.
 - 7) Laganim pritiskom na krilca držača LED modula (push-fix), te njihovim skupljanjem, utisnite push-fix kroz rupu na nosaču te ga tako izbacite van. Učinite tako za sve push-fixeve i oslobodit ćete LED modul.
 - 8) Spojiti sve komponente nazad u svjetiljku da bi svjetiljka ispravno funkcionirala.
 - 9) Vratiti sklopku u radno stanje kako bi doveli napajanje do svjetiljke.
-

Instructions for dismantling the light source and pre-connected device

Applicable to: Intab

- 1) Turn off the switch so that the lamp is not under voltage during disassembly.
- 2) Move the lens to one side, which reveals the screw with which the mask is connected to the lamp. Do the same on the other side in order to remove the mask from the lamp.
- 3) Unscrew the screws that hold the LED module holder on the lamp. Then remove the LED module holder from the lamp.
- 4) Disconnect the power cable from the terminal by pressing the grippers of the terminal and pulling out the wires.
- 5) Disconnect the wire that is connected to each LED module and driver by pressing the wire gripper on the LED module/driver with a thin object.
- 6) Unscrew the nuts and/or screws holding the driver.
- 7) By gently pressing the wings of the LED module holder (push-fix), and by pulling them together, push the push-fix through the hole on the support and thus eject it. Do this for all push-fixes and you will free the LED module.
- 8) Connect all components back to the lamp to make the lamp work properly.
- 9) Return the switch to the working state to supply the power to the lamp.